

UCM-SERIES

PUBLIC ADDRESS AMPLIFIER



TYPE	MIXER AMPLIFIER
MODEL	UCM-204
POWER SUPPLY	AC 115V or 230V 50/60Hz , DC 12V
POWER OUTPUT	40W Max.
TOTAL HARMONIC DISTORTION	≥ 1 % @ 1 KHz
SENSITIVITY	1/4" PHONE JACK (UNBALANCED) MIC 1,2 4 mV @ 600Ω AUX 100mV @ 10KΩ
OUTPUT	100 V , 8Ω
SIGNAL TO NOISE RATIO	80 dB
FREQUENCY RESPONSE	50 Hz ~15K Hz ± 3dB
MEDIA FORMAT	WMA, MP3
TUNER RANGE	FM 87.5 ~ 108 MHz
ANTENNA INPUT	75 Ω
AC POWER CONSUMPTION	40 W @ RATED POWER
DC POWER CONSUMPTION	3A @ RATED POWER
DIMENSION	70mmX240mmX187mm(HWD)
WEIGHT	3 KGS
MOUNTING	FREE STANDING

PATECH