

QSM-SERIES

# PUBLIC ADDRESS AMPLIFIER



TYPE  
MODEL  
POWER SUPPLY  
POWER OUTPUT  
TOTAL HARMONIC DISTORTION  
SENSITIVITY

OUTPUT  
SIGNAL TO NOISE RATIO  
FREQUENCY RESPONSE  
AC POWER CONSUMPTION  
DC POWER CONSUMPTION  
DIMENSION  
WEIGHT  
MOUNTING

MIXER AMPLIFIER  
QSM-204  
AC 115V or 230V 50/60Hz , DC 12V  
40W Max.  
 $\geq 1\%$  @ 1 KHz  
1/4" PHONE JACK (UNBALANCED)  
MIC 1,2 4 mV @ 600Ω  
AUX 100mV @ 10KΩ  
100 V , 8Ω  
80 dB  
50 Hz ~ 15K Hz  $\pm$  3dB  
40 W @ RATED POWER  
3A @ RATED POWER  
70mmX240mmX187mm(HWD)  
3 KGS  
FREE STANDING

**PA**TECH